

## **Technical Data Sheet**

Pressure • Temperature • Humidity • Air Velocity • Airflow • Sound level

# **KIRAY 200** Infrared thermometer





## Distance from the target

Distance	150	300	900	mm
Diameter	5	10	30	mm
			D:S=30:1 50 mm at 7	1500 mm
h/A —				
ĽĽS 🗆				
ED				



Make sure that the target is larger than the size of the laser sighting.

Infrared thermometer **KIRAY 200** is an infrared thermometer used to diagnose, inspect and check any temperature. Thanks to its elaborated optical system, it allows an easy and accurate measurement of little distant targets. **KIRAY 200** instrument has an internal memory which can save up to 20 measurements.

N<sup>ew</sup> Ce

## Technical features

#### Instrument features

Spectral response	8 -14 µm		
Optical	D.S : 30:1 (50 mm at 1500 mm)		
Response time	Less than 1 second		
Temperature range	From -50 to +850°C		
Accuracy*	From -50 to -20°C : ±5°C		
Display resolution	From -20 to +200°C : $\pm 1.5\%$ of reading $\pm 2°C$ From +200 to +538 °C : $\pm 2\%$ of reading $\pm 2°C$ From +538 to +850°C : $\pm 3.5\%$ of reading $\pm 5°C$		
Display resolution			
Emissivity	(pre-set at 0.95)		
Over range indication	Display indication : « -0L » for a negative over range, « 0L » for a positive over range.		
Laser sighting	Wavelength : 630-670 nm Output < 1mW, Class 2 (II)		
Positive or negative			
temperature indication	Automatic (no indication for a positive		
	temperature)		
	<ul><li>(-) sign for a negative temperature</li></ul>		
Display	4 ½ digits with LCD backlighted display		
Auto-extinction	Automatic after 7 seconds of inactivity		
High/low alarm	.Flashing signal on display and beep signal with adjustable thresholds		
Power supply	Alkaline 9V battery		
Autonomy	38 h (inactive laser and backlight)		
	15 h (active laser and backlight)		
Use temperature	From 0 to +50°C		
Storage temperature	From -20°C to +60°C		
Relative humidity	From 10% to 90%RH in operating mode and		
	>80%RH in storage		
Dimensions	175 x 110 x 45 mm		
Weight	230 g (included battery)		
Memory	20 temperature values with unit of measurement		
	(°C or °F)		

\*Accuracy for an ambient temperature from 18 to 28  $^\circ C$  (with a relative humidity lower than 80% RH)

#### • Thermocouple K probe features

Temperature range	From -40 to +400°C
Display range	From -50 to +1370°C
Resolution	0.1°C
Accuracy	±1.5% of reading ±3°C
Cable length	1 m



- 1 Continuous measurement indicator
- 2 Technical unit (°C / °F)
- 3 Low battery indicator
- 4 Low alarm symbol
- 5 MAX, MIN, DIF (difference between MAX and MIN values), AVG (average), HAL (high alarm), LAL (low alarm), TK (TK temperature) and LOG (recorded value)
- 6 High alarm symbol
- 7 EMS, MAX, MIN, DIF, AVG, HAL, LAL, TK and LOG indicator
- 8 Temperature value
- 9 Current measurement indicator
- 10 HOLD indicator (fixed measurement)
- 11 Emissivity value
- 12 Laser in operation indicator

## KIRAY 200 buttons



- 1 Up button. It allows to increment emissivity and high/low alarm thresholds and to move to the next recorded value.
- 2 Set button. It allows to activate or deactivate laser and display backlight. It allows also to record a temperature.
- 3 Mode button. It allows to navigate through the modes (emissivity, max value, min value, difference, average, high alarm, low alarm, TK value and recorded values).
- 4 Down button. It allows to decrement emissivity and high/low alarm thresholds and to move to the previous recorded value.

### Infrared thermometer, how it work ?

Infrared thermometers can measure the surface temperature of an object. Its optic lens catches the energy emitted and reflected by the object. This energy is collected and focused onto a detector. This information is displayed as temperature. The laser pointer is only used to aim at the target.

4



#### This device meets with following standards' requirements.

- EN 50081-1 : 1992, Electromagnetic compatibility, Part 1
- EN 50082-1 : 1992, Electromagnetic compatibility, Part 2
  - Infrared sensor Emitted energy by the Laser sighting

#### www.kimo.fr



Distributed by :

866-327-8731 www.techniCAL-sys.com

